

Poly Trio Speakerphone–User Guide

Poly RealPresence Trio 8300, 8500, 8800, and C60 Models



Product Sheet: UCaaS)

UC Software 5.9.3 or later

This Quick Tips applies to the Polycom® RealPresence® Trio™ 8300, 8500, 8800 and C60 speakerphone models.

Enter Data

You can use the onscreen keyboard to enter information. To use the onscreen keyboard:

- Tap a text field or tap

Place Calls

You can place a call to contacts from Contacts, Recent Calls, or to a favorite.

To place a call:

- Do one of the following from the Home screen:
 - Tap Place a Call, enter the phone number, and tap
 - Tap a Favorite.
 - Tap **Contacts**, select a directory, select a contact, and tap **Dial**.
 - Tap **Recent Calls** and select a contact. The contact is dialed automatically.

Answer calls

You can answer or decline incoming calls.

To answer a call:

- Tap Answer.
- Tap Decline.

End Calls

You can only end active calls.

To end an active call:

- Tap Hang Up.
- To end a held call, resume the call first.

To end a held call:

- Tap Resume > Hang Up.

Hold and Resume Calls

You can place any active audio or video call on hold and resume the call when you are ready.

To hold a call:

- Tap Hold.

To resume a call:

- Tap Resume.

Initiate a 4-way Conference call

You can initiate a conference call with up to four contacts.

To initiate a conference call:

1. Call a contact.
2. Tap Add and enter your contact's number or select a contact from Contacts or Recent Calls.

The contact is added to the conference after answering. You can also join an active and held call into a conference call.

To join two calls into a conference call:

- On the Calls screen, select two calls and tap Merge Calls.

Manage Conference Calls

When you initiate a conference call, you can mute all participants, mute individual participants, or remove a participant from the call.

To mute all conference participants:

- Tap the conference name and tap **Mute All** to mute all participants.

To manage individual participants:

- Tap a participant, then do one of the following:
 - Tap **Far Mute** to mute the participant.
 - Tap **Hang Up** to remove the participant from the conference.

View Recent Calls

You can view placed, received, and missed calls.

To view recent calls:

- Tap Recent Calls.

View the Contact Directory

You can view and add contacts to the Contact Directory.

To view the Contact Directory:

- Navigate to **Contacts > Contact Directory**.

To add a contact to the Contact Directory:

1. In the Contact Directory, tap
2. Enter the contact's information and tap Save.

Poly Trio Speakerphone–User Guide

Poly RealPresence Trio 8300, 8500, 8800, and C60 Models





Product Sheet: UCaaS

Add a Favorite

You can add contacts as favorite, and all favorites display on the Home screen.

To add a favorite:


1. Navigate to **Contacts > Contact Directory** and select a contact.
2. On the **Details** screen, tap .


The **Favorites** icon changes to blue  and the contact is added to the Home screen. Contacts added as Favorites display first in the **Contact Directory**.

Mute the Microphone

You can mute your microphone at any time.

To mute your microphone:

- Tap  **Mute** or tap the **Mute** keys on the system or microphone.

The **Mute** icon changes to red  and the **Mute** keys glow red.

Adjust the Volume

You can adjust the volume of calls or the ringtone for incoming calls using the volume keys.

To adjust the volume:

- Tap the **+** volume up or **-** volume down buttons.

Connect a Bluetooth Device

If Bluetooth is enabled, you can pair and connect your Bluetooth-capable phone or tablet with the conference phone.

To connect a Bluetooth device:

- On your device, navigate to **Bluetooth** and select on the **Polycom Trio** in the list of available systems and devices.

Connect a Bluetooth Device using Near Field Communication (NFC)

If Bluetooth and NFC are enabled, you can connect your NFC-enabled Bluetooth phone or tablet with a Polycom Trio 8300, 8500, 8800 and C60 system.

To connect a Bluetooth device using NFC:

- Enable NFC on your device.
 - Go to **Settings > Advanced > Administrator Settings > NFC Mode**.
 - Press the NFC sensor to the left of the RealPresence Trio 8300, 8500, 8800, and C60 screen. The phone prompts you to confirm pairing.
- Tap and hold your device for two seconds above the NFC symbol on the system.
- Confirm that your device is paired and connected to the Polycom Trio 8300, 8500, 8800, and C60

Place a Call over Bluetooth

If your mobile phone is connected to the Polycom Trio system using Bluetooth or NFC, you can place a call on your mobile phone and use the system as the speakerphone for the call.

To place a call over Bluetooth:



1. On your mobile phone, place a call to a contact.
2. On the call screen, select the **Polycom Trio 8300, 8500, 8800 and C60** as your audio source.

Show Content

When a Polycom Trio Visual+ is connected to a monitor and paired with a Polycom Trio 8300, 8500, and 8800 system, you can show content locally.

If you do not have either application, you can download **RealPresence Desktop** from [Polycom Support](#) and **RealPresence Mobile** from your tablet's application store.

To show content using RealPresence Desktop

1. Open the desktop or mobile application.
2. Navigate to  **Settings > SmartPairing**.
3. Click or tap the check boxes for **Enable SmartPairing** and **Auto Detection** and click **OK** or **Done**.
4. Select  and select **Share Content**.
5. Select your system's name or IP address and select **Pair**.

If your system is not listed, enter your system's IP address and select **Pair**.

In **RealPresence Mobile**, tap **Manual Pairing** then enter your system's IP address and tap **Go**.

6. Choose a monitor or application to share.

In **RealPresence Desktop**, the content is displayed automatically.

7. In **RealPresence Mobile**, tap  to show content.

Poly Trio Speakerphone–User Guide













Poly RealPresence Trio 8300, 8500, 8800, and C60 Models



Product Sheet: UCaaS

Polycom RealPresence Trio Phones Icons and Status Indicators

The following table displays the icons and status indicators that display on Polycom Trio series phones.

Icon	Description	Icon	Description
	Registered Line		Do Not Disturbed enabled
	Unregistered Line		Call Forwarding enabled
	Active Call		Wireless status
	USB device attached		Paired Device
	Missed Call		Bluetooth
	Placed Call		Received Call